

macOS, iTerm, ZSH

iTerm2 Customize on macOS

Preparation

1. get and install iTerm
2. install brew
3. get and install font
4. get solarized theme
5. install zsh, oh-my-zsh

Settings

1. setting on iterm
 1. theme
 2. text
2. setting zsh as default
3. set theme in ~/.zshrc
4. set other stuffs in ~/.oh-my-zsh/themes/agnoster.zsh-theme

```
echo "\ue0b0 \u00b1 \ue0a0 \u27a6 \u2718 \u26a1 \u2699"
```

Others

프롬프트 사용자 이름 삭제

```
$ vim ~/.zshrc
```

```
prompt_context() {  
  if [[ "$USER" != "$DEFAULT_USER" || -n "$SSH_CLIENT" ]]; then  
    prompt_segment black default "%(!.%{F{yellow}}).)$USER"  
  fi  
}
```

Word jump 활성화하기

word jumps 활성화 하기

- 기본적으로 oh-my-zsh에서는 `option + 방향키` 조합의 단어별 이동이 불가능하다. 이를 수정하려면 별도의 설정수정이 필요하다.
- iTerm -> Preferences -> Profiles -> Keys 로 이동한다.
- `+` 버튼을 누르고 아래 설정을 추가한다.

```
```shell
Option + right
↩→
Send Escape Sequence
f
Option + left
↩←
Send Escape Sequence
b
```

# Syntax Highlighting

```
설치
$ brew install zsh-syntax-highlighting

~/.zshrc 에 아래 문구 추가
source /usr/local/share/zsh-syntax-highlighting/zsh-syntax-highlighting.zsh
```

# 테마변경

```
vi .zshrc
ZSH_THEME="robbyrussell"
```

# Multiline Prompt

```
vi ~/.oh-my-zsh/themes/agnoster.zsh-theme

Main prompt
build_prompt() {
 RETVAL=$?
 prompt_status
 prompt_virtualenv
 prompt_context
 prompt_dir
 prompt_git
 prompt_bzr
 prompt_hg
 prompt_newline # 멀티라인 적용
 prompt_end
}

멀티라인 적용, 커버모양 변경
prompt_newline() {
 if [[-n $CURRENT_BG]]; then
 echo -n "%{k%F{$CURRENT_BG}%}$SEGMENT_SEPARATOR
%(?.%F{$CURRENT_BG}.%F{red})$SEGMENT_SEPARATOR" # }%f"

 else
 echo -n "%{k%}"
 fi

 echo -n "%{f%}"
 CURRENT_BG=' '
}
```

From:  
<http://dev.theta5912.net/> - **reth.dev**

Permanent link:  
[http://dev.theta5912.net/doku.php?id=public:computer:iterm\\_customize&rev=1521278174](http://dev.theta5912.net/doku.php?id=public:computer:iterm_customize&rev=1521278174)

Last update: **2021/01/20 17:48**

